

LED RETROFIT LAMPS

120VAC Operation
 1.2 Watts per Lamp
 Screw in Base



DESCRIPTION

The AimLite RTRO exit sign replacement lamp kit provides exceptional energy and maintenance savings over traditional incandescent type lamps. Each RTRO lamp consumes just 1.2 watts of AC power and is designed utilizing long-life maintenance-free LEDs. The twenty-six high brightness LEDs are arranged in a "U" shape in order to optimize the light distribution. The thin-line LED housing is made from an advanced technopolymer that can be rotated to align with the faceplate of the exit sign.

ELECTRICAL

- 120VAC 60Hz input
- 1.2W power consumption per lamp
- 26 High brightness LEDs per lamp
- Integral current limiting and surge absorbing capacitors insure flicker free, long-life operation

FEATURES

- Lightweight and durable white technopolymer housing construction
- Housing can be rotated 180° in either direction to align with exit sign faceplate
- Integral candelabra base standard
- Optional screw on bases available for:
 - Intermediate Base
 - Medium Base
 - DC Bayonet Base
- Slim design to allow installation into narrow width exit signs

ORDERING GUIDE

Series	Input Voltage	Base Tyoe
RTRO	120 - 120VAC 60Hz	U - Universal (kit include candelabra, intermediate & double contact bayonet) M - Medium